

QUANTUM SPARK 1500 系列 Quick Setup Guide



目錄

	硬體面板	
<u> </u>	安裝及設定	
Ξ.	進階設定	14
四.	進階設定	14

本文件包含的專屬資訊受到著作權法所保護。未經鉅立資訊股份有限公司書 面同意,不得複印、複製本文件的任何部份,或將本文件的任何部份翻譯成 其他語言。如果本文件中針對特定管轄地區的公認語言版本與另一個版本有 出入,以針對特定管轄地區的公認語言版本為準。 一. 硬體面板



序號	項目	說 明
1	USB 3.0	用於軟體下載
2	LAN Port 1-5/WAN Port1-1G	1-5 為 LAN 連接埠,LAN2 為同步(Sync)埠,WAN 連接 埠
3	Console Port	Speed:115200
4	Power DC12V	電源線接孔
5	Factory Default	持續長壓至 Port LED 熄 滅・約為 12 秒・可將設備 還原為其出廠預設值
6	Power Button	按下以開啟或關閉硬體設備

二. 安裝及設定

- ・步驟 1:將網路線連接電腦及防火牆 LAN port ,將電腦網段設為
 【192.168.1.0/24】
- ・步驟 2:開啟支援的網頁瀏覽器(Edge、Chrome、Firefox或 Safari),在網址
 輸入【https:192.168.1.1:4434】(預設 Port 為 4434)

←
 一
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇
 〇

○ 輸入網址後會出現 [圖一] 畫面,是因為電腦無法識別該憑證,無須理會;
 請繼續選取進階 (如圖一紅圈處),繼續前往 192.168.1.1(如圖二紅圈處)。

(圖一)	
	您的連線並非私人連線
	收整当可能自管就後 192.168.1.1 维 取然的資料 (例如必請。訊息或信用卡) ·
	NET:EUR.CERT_AUTI ORITY_INVALID
(圖二)	
	您的連線並非私人連線
	攻撃者可能會嘗試從 192.168.1.1 竊取您的資料 (例如密碼、訊息或信用卡)・
	NET::ERR_CERT_AUTHORITY_INVALID
	■ 「幕線進階 上一歩
	此伺服器無法證明其是 192.168.1.1;您電腦的作業系統不信任其安全性憑證。這可能是由 於設定錯誤或攻擊者攔截您的連線造成的。
	<u> 繼續前往 192.168.1.1 (不安全)</u>

·步驟 3:第一次進入後會有 Wizard,點選 Next 進入下一步 (如下圖紅圈處)



·步驟 4:設定密碼,輸入管理者的帳號與密碼

Authentication Details Change the default administrator name and set the password: Administrator name: admin Password: Confirm password: Image: Inforce password complexity on administrators It is strongly recommended to use both uppercase and lowercase characters as well as one of the following characters in the password: Image:	CHECK POINT 1500 APPLIANCE WIZARD ? Hel							
Change the default administrator name and set the password: Administrator name: admin Password:	Authentication Det	Authentication Details						
Administrator name: admin Password: Password: Confirm password: Enforce password complexity on administrators It is strongly recommended to use both uppercase and lowercase characters as well as one of the following characters in the password: !@#\$96^&*()=+;;	Change the default administrator name and set the password:							
Password: Password strength: Confirm password: Strong Enforce password complexity on administrators It is strongly recommended to use both uppercase and lowercase characters as well as one of the following characters in the password: !@#\$%^&*()=+:; Help us improve product experience by sending data to Check Point Step 1 of 9 Authentication	Administrator name:	admin						
Confirm password:	Password:		Password strength:	ong				
Enforce password complexity on administrators It is strongly recommended to use both uppercase and lowercase characters as well as one of the following characters in the password: !@#\$%^&*()=+:; Help us improve product experience by sending data to Check Point Step 1 of 9 Authentication < Back	Confirm password:							
It is strongly recommended to use both uppercase and lowercase characters as well as one of the following characters in the password: !@#\$%^&*()=+:; Help us improve product experience by sending data to Check Point Step 1 of 9 Authentication < Back Next > Quit	Enforce password com	nplexity on administrators						
Help us improve product experience by sending data to Check Point Step 1 of 9 Authentication < Back	It is strongly recommended to use both uppercase and lowercase characters as well as one of the following characters in the password: !@#\$%^&*()=+:;							
Step 1 of 9 Authentication < Back Next > Quit	Help us improve product experience by sending data to Check Point							
	Step 1 of 9 Authentication	n	< Back	Next > Quit				

・步驟 5:設定時間與日期,上列選項為手動設定,建議使用下列的 NTP
 選項設定(如下圖紅框處),如有自己的 NTP Server 也可以手動輸入

CHECK POINT 1500 APPL	CHECK POINT 1500 APPLIANCE WIZARD ? Help				
Appliance Date an	Appliance Date and Time Settings				
O Set time manually					
Date:	Thursday, June 23, 2022	÷			
Time:	3 : 18 PM 🔻				
Time zone:	(GMT+08:00) Taipei	~			
 Use Network Time Pro First NTP server: Second NTP server: Time zone: 	•				
Step 2 of 9 Date and Time Settings < Back					

・步驟 6:設定設備名稱與網域名稱,如沒有名稱可以直接點選 Next (如下圖紅圈處)

CHECK POINT 1500 A	PPLIANCE WIZARD	? Help
Appliance Nam	e	
Non-Tank		
Appliance Name:	Gateway-ID-7F9C9FF6	
Domain name:	Field is not mandatory	
	Example: mycompany.com	
Step 3 of 9 Appliance	e Name	< Back Next > Quit

·步驟7:設定管理模式單點管理/中心端管理



·步驟 8:設定 WAN Port · 針對網路環境狀況使用 DHCP 或 Static IP

○ 網路線連接於 WAN Port;另一端接於數據機或是其他對外網路 的網路設備

CHECK POINT 1500 APPLIANCE WIZARD ? Help					
Internet Connection			g		
 Configure Internet connection type: 	•				
Connection type: DHCP Configure Internet connection later		Connec	t		45 WAN
Step 5 of 9 Internet Connection		< Back	Nex	t > Quit	

O 使用 Static IP 設定畫面

CHECK POINT 1500 APPLIANCE WIZARD 3 Help					
Internet Connection		SOFTW	RECK Point"		
• Configure Internet connection					
Connection type:	Static IP	•			
IP address:	220.128.138.23		3 - 4	- 5 WAN	
Subnet mask:	255.255.255.0				
Default gateway:	220.128.138.254				
First DNS server:	8.8.8.8			Ţ	
Second DNS server:					
	Connec	t	·		
 Configure Internet connection later 					
🔗 WAN link is up					
Step 5 of 9 Internet Connecti	< Back	Next >	Quit		

·步驟 9: 設定本機 IP 及 LAN Port, Check Point 預設會開啟

DHCP Server · 範圍為 192.168.1.110 ~ 192.168.1.210 · 請確認連接設備是否拿到該網段 IP · 如不需使用此功能 · 您可將 Enable 前方的勾選取消即 Disable 此功能

CHECK POINT 1500 AF	PPLIANCE WIZARD			? Help	
Local Network			SOFTWAR		
LAN Settings	LAN Settings				
✓ Enable switch on	LAN ports			1 2 3	4 5 WAN
Network name:	LAN Switch				
IP address:	192.168.1.1				
Subnet mask:	255.255.255.0				
DHCP Settings				LAN switch	
DHCP Server:	Enabled 🔹			Traffic between LA inspect	AN ports is not ted
DHCP range:	192.168.1.1	: 192.168.1.254			
The device IP address	is automatically exclu	ided from the DHCP	^o range		
Exclusion range:	not mandatory	: not mandatory	/		
Step 6 of 9 LAN			< Back	Next >	Quit

·步驟 10: 設定管理者進入,保持預設,如有特殊需求可以自行調整能

CHECK POINT 1500 APPLIANCE WIZARD			? Help
Administrator Access		Ch SOFTW	
Select the sources from which to allow administrator acces	ss		
✓ LAN ✓ VPN Internet			
Access from the above sources is allowed from			
O Any IP address			
O Specified IP addresses only			
 Specified IP addresses from the Internet and any IP address from other sources 			
★ New × Delete			
No Items Found			6
Step 7 of 9 Administrator Access	< Back	Next >	Quit

·步驟 11: 選取要在此硬體設備啟動的軟體功能,預設全開

CHECK POINT 15	CHECK POINT 1500 APPLIANCE WIZARD (7) Help					
Software Bla	Software Blades Activation					
Select the Softwa	are Blades you wis	h to activate				
ACCESS CONTRO	L		VPN			
✓		√ []=	v 🌐			
Firewall	Applications & URL Filtering	User Awareness	Remote Access	Site To Site VPN		
THREAT PREVENT	FION					
☑ ●	✓ 🗞	✓	v 🕄	\checkmark		
Intrusion Prevention (IPS)	Anti-Virus	Anti-Bot	Threat Emulation	Anti-Spam		
Step 9 of 9 Software Blades Activation < Back Next > Quit						

O 檢視之前做的設定,確認後按下 Finish (如下圖紅圈處),完成

「首次設定精靈」。

CHECK POINT 1500 APPLIANCE WIZARD				
The First Time Configu	The First Time Configuration Wizard has completed			
Administrator name: System time: Appliance name:	admin Friday, April 29, 2022 02:07 PM Gateway-ID-7F9C9FF6 (1550 Appliance)			
Internet: License:	 Connected Obtained 			
Local network:	192.168.100.253 / 255.255.255.0 DHCP server is disabled A secondary IP address was set on LAN1 Switch i			
Security policy mode:	Locally managed			
Active Software Blades:	Firewall, Application Control, URL Filtering, User Awareness, Remote Access, Site To Site VPN, Intrusion Prevention (IPS), Anti-Virus, Anti-Bot, Threat Emulation, Anti-Spam			
	\frown			
	< Back Finish			

三. 設置完成

將電腦網卡 IP 修改為跟防火牆同一網段後,在瀏覽器輸入新設定的 IP,
 登入網頁確認,狀態設置完成



四. 進階設定

• 完成以上步驟 Check Point 防火牆基本設置已經完成,如需後續 Policy 設 定請參照下列網址

Configuring the Firewall Access Policy and Blade (checkpoint.com)